




BRAND Visual Comfort Modern

DESCRIPTION

This 300 watt 12 volt remote magnetic transformer converts standard 120 or 277 volt line voltage to 12 volts, providing the necessary voltage for powering a Monorail, Kable Lite, Wall Monorail or Freejack low voltage lighting system. Includes 16 foot cord with plug. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset by simply flipping the wall switch off and back on. Must be installed in a remote, but accessible location such as above the ceiling or a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. ETL listed. 10.6 inch length x 4.3 inch width x 4.1 inch height.



SHADE COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Magnetic
DIMENSIONS	10.6"L x 4.3"W x 4.1"H
LAMP	N/A
SPEC #	TLG9452



COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE