




BRAND Visual Comfort Modern

DESCRIPTION

This 300 watt 24 volt remote magnetic transformer converts standard 120 or 277 volt line voltage to 24 volts, providing the necessary voltage for powering a Monorail, Kable Lite, Wall Monorail or Freejack low-voltage lighting system. Includes 16 foot cord with plug. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset. Must be installed in a remote, but accessible location such as above the ceiling or in a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. 10.6 inch length x 4.3 inch width x 4.1 inch height.



SHADE COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Magnetic
DIMENSIONS	10.6"L x 4.3"W x 4.1"H
LAMP	N/A
SPEC #	TLG9454



COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE